MM-100X100-AP

(60 lb. WLL)

VESA TO SPEAKER MOUNT ADAPTER


MULTIMOUNT®



Use this adapter for mounting speakers with the 100X100mm square mounting hole pattern to the rectangular hole pattern of the MultiMount. The adapter first receives the 5/16" screws in the rectangular hole pattern then is attached to the loudspeaker using the included metric screws. That means that the 5/16" screws are

secure the MultiMount over the protruding 5/16" screws using the included flat washers and locking nuts.

protruding out and the last step is to



STANDARD FEATURES:

- Adapts standard speaker mounting hole patter to the 100x100mm vesa pattern.
- Adapts to MultiMount product
- Easy 4 screw installation

ACCOMMODATES:

- MultiMount MM-022-BT
- MultiMount MM-024-BT
- MultiMount MM-060-BT

OPTIONAL ACCESSORIES:

Optional safety cables available

SPECIFICATIONS:

Material: Structural Steel Alloy

Finish: Powder Coat

Color: Black

WLL: 60 lbs. (27.2 Kg) max.

Design Factor: 10:1 ratio

Net WGT: 2 lbs. (.9 Kg) each

Shipping WGT: 5 lbs. (2.3 Kg) each

Pack Count: 1 unit/carton

*WLL = Working Load Limit

PACKAGE CONTENTS:

1 pc Mounting Plate

4 pcs 5/16" x 1" Screws


4 pcs M10X40mm Screws

4 pcs 5/16" Flatwasher


4 pcs 5/16" Nyloc Nuts

DIMENSIONS:

MM-100x100-AP




MM-022 MM-024 / MM-060



Front View

Side View





Adaptive Technologies Group

1635 E. Burnett Street | Signal Hill, CA 90755 USA Ph: 562.424.1100 | Fax: 562.424.3520 www.adapttechgroup.com



ALWAYS INSTALL SAFETY CABLES

WARNING: Mounting and/or suspension of audio and video equipment requires experienced professionals. Improperly installed loudspeakers can result in property damage, personal injury and/or liability to the installing contractor.